



59.95 EUR  
 incl. 19% VAT, plus [shipping](#)

Support: [Heatsink-Height](#)

Minimum order quantity : 10 units !

The Intel® Desktop Board D201GLY2 is an innovative solution for the sub-value market segment. With an Intel® Celeron® processor and graphics integrated on the board, this board enables easy system integration and helps you to achieve a lower system cost. This board has 10/100 LAN, support up to six Hi-Speed USB 2.0 ports and 2 SATA (1.5 GB/s), providing both connectivity and ease of use for your computing needs such as email and Internet access, instant messaging and Voice Over IP (VoIP).

The Intel Desktop Board D201GLY2 is built in smaller uATX-Compatible form factor providing lower power consumption and passive thermal solution.

Form Factor	uATX (6.75 inches by 6.75 inches [171.45 millimeters by 171.45 millimeters]) (ITX compatible)
Processor	Integrated Intel® Celeron® 220 processor (1.2 Ghz) with a 533 MHz system bus
Memory	One 240-pin DDR2 SDRAM Dual Inline Memory Module (DIMM) sockets Support for DDR2 677/533/400 MHz DIMMs Support for up to 1 GB of system memory
Chipset	SiS* SiS662 Northbridge SiS* SiS964L Southbridge
Audio	ADI* AD1888 audio codec
Video	Integrated SiS Mirage* 1 graphic engine
I/O Control	Winbond* W83627DHG-B based Legacy I/O controller for hardware management, serial, parallel, and PS/2* ports
LAN Support	10/100 Mb/s LAN subsystem using the Broadcom* LAN adapter device
Peripheral Interfaces	Six USB 2.0 ports One parallel ATA IDE interface with UDMA 33, ATA-66/100/133 support <b>Two SATA ports</b> One serial port One parallel port PS/2* keyboard and mouse ports
Expansion Capabilities	One PCI Conventional* bus connector

**Note** : The CPU heatsink has a height of 45mm. That's why it does not fit into every enclosure.

Compatible with :

- Voom
- Voom-2
- M300(-LCD)
- Travla C137

Not compatible with :

- M200(-LCD)
- Morex enclosures (without PCI slot)

**PicoPSU & M3-ATX** : You can only directly stick in the standard picoPSU-120 power supply. Other picoPSU models and M3-ATX can only be connected with an additional ATX extension cable.

For Operating you need a P4 adapter or a PSU with P4 connector