






#### 139.95 EUR

incl. 19% VAT, plus shipping

- Intel WiFi, Intel WiDi!
- Dual Gigabit LAN!
- Gigabyte Features!
- NVMe M.2 slot!

- Supports 7th/ 6th Generation Intel® Core™ Processors
- Dual Channel Non-ECC Unbuffered DDR4, 2 DIMMs
- Intel® USB 3.1 Gen 1 with USB Type-C™
- Intel® Optane™ Memory Ready
- Ultra-Fast M.2 with PCIe Gen3 x4 & SATA interface
- ALC1220 120dB SNR HD Audio with Smart Headphone Amp
- 802.11ac Dual Band 867Mbps wireless supports MU-MIMO and BT4.2
- Dual Intel® GbE LAN with cFosSpeed Internet Accelerator Software
- Smart Fan 5 features Multiple Temperature Sensors and Hybrid Fan Headers
- Ultra Durable™ Metal Shielding over PCle Slots
- GIGABYTE UEFI DualBIOS™
- APP Center Including Cloud Station™ Utility




[http://www.minipc.de/catalog/il/1481]

mini	(PC).de
111111111	(PL/de

LAN

1. Support for 7th and 6th generation Intel® Core™ i7 processors/Intel® Core™ i5 processors/ Intel® Core™ i3 processors/Intel® Pentium® processors/Intel® Celeron® processors in the LGA1151 package CPU 2. L3 cache varies with CPU (Please refer "CPU Support List" for more information.) Chipset 1. Intel® H270 Express Chipset 1. 2 x DDR4 DIMM sockets supporting up to 32 GB of system memory \* Due to a Windows 32-bit operating system limitation, when more than 4 GB of physical memory is installed, the actual memory size displayed will be less than the size of the physical memory installed. 2. Dual channel memory architecture 3. Support for DDR4 2400\* / 2133 MHz memory modules Memory 4. Support for ECC Un-buffered DIMM 1Rx8/2Rx8 memory modules (operate in non-ECC mode) 5. Support for non-ECC Un-buffered DIMM 1Rx8/2Rx8/1Rx16 memory modules 6. Support for Extreme Memory Profile (XMP) memory modules \* To support 2400 MHz or XMP memory, you must install a 7th generation processor. (Please refer "Memory Support List" for more information.) Integrated Graphics Processor: 1. 1 x DVI-D port, supporting a maximum resolution of 1920x1200@60Hz 2. 2 x HDMI ports, supporting a maximum resolution of 4096x2160@24Hz or 2560x1600@60Hz \* Support for HDMI 1.4 version. **Onboard Graphics** 3. Support for up to 3 displays at the same time \* To set up a triple-display configuration, you must connect a D-Sub monitor using a DVI-to-D-Sub adapter. 4. Maximum shared memory of 1 GB 1. Realtek® ALC1220 codec 2. High Definition Audio Audio 3. 2/4/5.1/7.1-channel 4. Support for S/PDIF Out

1. 2 x Intel® GbE LAN chips (10/100/1000 Mbit)



[http://www.minipc.de/catalog/il/1481]

## 1. Wi-Fi 802.11 a/b/g/n/ac, supporting 2.4/5 GHz Dual-Band

#### Wireless

#### Communication module

#### 2. BLUETOOTH 4.2, 4.1, BLE, 4.0, 3.0, 2.1+EDR

- 3. Support for 11ac wireless standard and up to 867 Mbps data rate
  - \* Actual data rate may vary depending on environment and equipment.

## **Expansion Slots**

1. 1 x PCI Express x16 slot, running at x16
 (The PCIEX16 slot conforms to PCI Express 3.0 standard.)

2. 1 x M.2 Socket 1 connector for the wireless communication module (M2\_WIFI)

#### Chipset:

## Storage Interface

- 1. 1 x M.2 connector on the back of the motherboard (Socket 3, M key, type 2260/2280 SATA and PCIe x4/x2 SSD support)
- 2. 6 x SATA 6Gb/s connectors
- 3. Support for RAID 0, RAID 1, RAID 5, and RAID 10


#### Chipset:

# USB

- 1. 2 x USB 2.0/1.1 ports available through the internal USB header
- 2. 6 x USB 3.1 Gen 1 ports (4 ports on the back panel, 2 ports available through the internal USB header)
- 3. 1 x USB Type-C<sup>™</sup> port on the back panel, with USB 3.1 Gen 1 support
- 1. 1 x 24-pin ATX main power connector
- 2. 1 x 4-pin ATX 12V power connector
- 3. 6 x SATA 6Gb/s connectors
- 4. 1 x M.2 Socket 3 connector on the back of the motherboard
- 5. 1 x CPU fan header
- 6. 1 x system fan header

#### Internal I/O Connectors

- 7. 1 x front panel header
- 8. 1 x front panel audio header
- 9. 1 x USB 3.1 Gen 1 header
- 10. 1 x USB 2.0/1.1 header
- 11. 1 x S/PDIF Out header
- 12. 1 x Clear CMOS jumper
- 13. 1 x chassis intrusion header



[http://www.minipc.de/catalog/il/1481]

-	( <b>PC)</b> .de	
[[]][[]]		à
	( ) ·	•

- 1. 1 x PS/2 keyboard/mouse port 2. 2 x HDMI ports 3. 2 x SMA antenna connectors (2T2R) 4. 1 x DVI-D port **Back Panel Connectors** 5. 4 x USB 3.1 Gen 1 ports 6. 1 x USB Type-C<sup>™</sup> port, with USB 3.1 Gen 1 support 7. 2 x RJ-45 ports 8. 1 x optical S/PDIF Out connector 9. 5 x audio jacks (Center/Subwoofer Speaker Out, Rear Speaker Out, Line In, Line Out, Mic In) 1. iTE® I/O Controller Chip I/O Controller 1. System voltage detection 2. CPU/System temperature detection H/W Monitoring 3. CPU/System fan speed detection 4. CPU/System fan speed control \* Whether the fan speed control function is supported will depend on the cooler you install. 1. 2 x 128Mbit flash 2. Use of licensed AMI UEFI BIOS 3. Support for DualBIOS™ 4. PnP 1.0a, DMI 2.7, WfM 2.0, SM BIOS 2.7, ACPI 5.0 1. Support for APP Center \* Available applications in APP Center may vary by motherboard model. Supported functions of each application may also vary depending on motherboard specifications. 3D OSD @BIOS Ambient LED AutoGreen BIOS Setup Color Temperature Cloud Station EasyTune Easy RAID Fast Boot Game Boost ON/OFF Charge Platform Power Management Smart Backup Smart Keyboard Smart TimeLock System Information Viewer USB Blocker V-Tuner
- **Unique Features**

**BIOS** 

- 2. Support for Q-Flash
- 3. Support for Smart Switch
- 4. Support for Xpress Install



Gigabyte GA-H270N-WIFI (für i3, i5, i7 [Sockel LGA1151], H270 Express, 2x LAN, 2x HDMI, WLAN/BT, NVMe M.2)

[http://www.minipc.de/catalog/il/1481]

Bundle Software	1. Norton <sup>®</sup> Internet Security (OEM version)
	2. Intel® Wireless Display
	3. Intel® Optane™ Memory Ready
	4. cFosSpeed
	1. Windows® 10 64-bit (for 7th Generation Intel® Processors)
Operating System	<ol> <li>Windows® 10 64-bit / Windows® 8.1 64-bit / Windows® 7 32-bit / 64-bits (for 6th Generation Intel® Processors) * Please download the "Windows USB Installation Tool" from GIGABYTE's website and install it before installing Windows 7.</li> </ol>
Form Factor	1. Mini-ITX Form Factor; 17.0cm x 17.0cm
Remark	Due to different Linux support condition provided by chipset vendors, please download Linux driver from chipset vendors' website or 3rd party website.
. Comani	2. Most hardware/software vendors may no longer offer drivers to support Win9X/ME/2000/XP. If

drivers are available from the vendors, we will update them on the GIGABYTE website.