



239.00 EUR  
incl. 19% VAT, plus [shipping](#)

- AMD G-Series APU + Hudson M1 Chipset
- Support AMD eOntario (G-Series) T40E Dual core APU
- Support DirectX 11 3D Graphics Acceleration
- Support 2 \* Gigabit LAN
- Support DVI-I Output
- Equipped with 802.11 b/g/n WiFi card & Internal Antenna (JBC361F35W-B only)
- Support 2.5" SATA HDD
- Support Mini PCI-E socket (alternative with mSATA)
- Small size and provide VESA mount bracket

<b>Model No:</b>	<b>JBC361F35-T40E-B / JBC361F35W-T40E-B</b>
<b>Motherboard Specification</b>	
<b>CPU</b>	AMD eOntario (G-Series) Dual core T40E 1.0GHz APU
<b>Chipset</b>	AMD Brazos G-Series APU + Hudson M1 Chipset
<b>Memory</b>	1 * SODIMM Sockets for un-buffered Single Channel 64-bit DDR3 800-1066 SDRAM up to 4 GB
<b>Expansion Slots</b>	1 * Mini PCI-E
<b>LAN</b>	2 * Realtek RTL8111EVL PCI-E Gigabit Ethernet LAN
<b>Audio</b>	VIA VT1705 HD Audio CODEC with 4-Channel
<b>Storage</b>	2 * Serial ATA3 6Gb/s connector 1 * mSATA (alternative with Mini PCI-E)
<b>BIOS</b>	AMI EFI 16MB SMT Flash ROM
<b>Form Factor</b>	3.5" SBC (148mm x 102mm)
<b>Barebones Specification</b>	
<b>Product size</b>	152.6 (L)x110 (W)x34.8 (D)mm
<b>Specs Devices</b>	1 x 2.5"HDD Drive Bay (Only support SATA 2.5"HDD)
<b>Colors</b>	Black
<b>Front I/O Port</b>	1 * Power button
<b>Rear I/O Port</b>	4 * USB 2.0 ports 1 * 12V DC jack 2 * RJ-45 port (Gigabit LAN) 1 * Line-out port and 1 * DVI-I port
<b>Power supply</b>	+12V DC-IN Power

<p><b>Accessory</b></p>	<p>60W AC-DC Adapter * 1 &amp; Power Cord * 1          CD * 1 &amp; Manual * 1          DVI-I to CRT Converter * 1          Stand * 2          WI-FI antenna * 1 ■ <b>JBC361F35W -BW only</b> ■          Wall Mount Bracket * 2 (Optional)          VESA Mount Bracket * 1</p>
<p><b>Application</b></p>	<p>Kiosk, Digital Signage, Gaming machine, Set Top Box, Thin Client, Car PC Application, Smart Mini PC, Factory Automation</p>
<p><b>Packing</b></p>	<p>Color Box Dimension ■ 417(W) * 137(D) * 296(H)mm          Gross Weight ■ 2.6KG          Net Weight ■ 2.1KG</p>