



419.00 EUR

incl. 19% VAT, plus [shipping](#)**500W DC ATX P4 Power Supply (9-18VDC)**

Now you can power every PC in your car. 500W power and Pentium-4 connector are giving you all possibilities !
The ATX connector has 24 pins. Along with the power supply there is a 24pol to 20pol ATX adapter included.

Dimensions	150mm[W] × 170mm[L] × 86mm[H] Standard ATX PS/2 size
Weight	2.67 kgs
Input Voltage Range	9 - 18VDC
Output Power maximum	500W
Output Power maximum (rails)	+3.3V : 35A +5.0V : 60A +12.0V : 35A
Remote sensing	+5V and +3.3V
Over Power Protection	Load over 130%±10% of max. output power : shutdown
Over Voltage Protection	+5V, +12V & +3.3V Auto-recovery
Short Circuit Protection	Main outputs shutdown and latch off
Over Temperature Protection	OTP Level is set at 110°C
Operating Temperature	-20°C ~ +70°C
Storage Temperature	-40°C~+80°C
Cooling	Build-in One 80x80x25mm Ball Bearing Fan with max. air flow 42CFM

Note : Minimum power of 60W must be drawn at system startup time !